

RSA Standard Series

Ceramic Bushing Insulators



Description

Transformer bushing insulators are applied as a structure, carrying on conductor through a partition such as transformer tank and insulating it, incorporating the means of attached flange to the partition for medium voltage level.

For Entire Range of Bushings Ratings from - 1 Kv to 72 Kv & - 100 Amp. to 10,000 Amp.

All Ares Insulator transformer bushing insulators are made of ceramic materials according to IEC 672. Other Transformer bushing custom-made insulators can be supplied upon customer's request and specifications.

Specifications

| Part Number | U.m (kV) | Ir (A) | Tank Hole Size (mm) | CD (mm) | Stem Connect |
|-------------------|----------|--------|---------------------|---------|--------------|
| RSA 1/160 | 1 | 160 | 31 | - | - |
| RSA 1/250 | 1 | 250 | 31 | - | - |
| RSA 1/330 | 1 | 330 | 31 | - | - |
| RSA 1/500 | 1 | 500 | 45 | - | - |
| RSA 1/630 | 1 | 630 | 45 | - | - |
| RSA 1/850 | 1 | 850 | 50 | - | - |
| RSA 1/1250 | 1 | 1250 | 50 | - | - |
| RSA 1/1600 | 1 | 1600 | 70 | - | - |
| RSA 1/2500 | 1 | 2500 | 70 | - | - |
| RSA 1/2900 | 1 | 2900 | 70 | - | - |
| RSA 1/3500 | 1 | 3500 | 70 | - | - |
| RSA 3/250 | 3.6 | 250 | 40 | - | - |
| RSA 3/330 | 3.6 | 330 | 40 | - | - |
| RSA 3/630 | 3.6 | 630 | 41 | - | - |
| RSA 1/250 | 1 | 250 | 31 | - | - |
| RSA 1/630 | 1 | 630 | 45 | - | - |
| RSA 1/1250 | 1 | 1250 | 50 | - | - |