

## COPPER CONNECTOR

### SPLIT BOLT CONNECTOR (T/J) - COPPER

#### Description

It is suitable for the sequence and transportation of all kinds of conductor in electric connecting, made of copper, brass, and copper plating.



Models	L (mm)	M (mm)	C (mm)	A (mm)
T/J-16	20	M17×2.5	6	18
T/J-25	27	M19×2.5	7	20
T/J-35	35	M21×2.5	7	22
T/J-50-70	42	M23×2.5	11	24
T/J-95-120	45	M25×2.5	14	26
T/J-150-185	60	M29×2.5	17	30
T/J-210-240	62	M31×2.5	20	32

### COMPRESS CONNECTOR (CCT) - COPPER



Models	Suitable Section of Conductor (mm <sup>2</sup> )	A	H	L	b	C
CCT-10	7.5-14	9.5	6.2	12	1.6	4
CCT-16	14.5-16	11.8	7.8	13	2	5
CCT-20	16.5-20	12.8	9.7	13	2.9	5.4
CCT-26	21-26	14.7	10.9	16	3.2	6.5
CCT-44	27-44	19	14.4	20	4	8.5
CCT-60	45-60	21	15.1	22	4	9.7
CCT-76	61-76	24.4	17.6	22	5	10.8
CCT-98	77-98	27.8	18.8	25	5	12.8
CCT-122	99-122	29.8	21.2	26	5.5	13.5
CCT-154	123-154	34	24.4	28	6	17
CCT-190	155-190	37	25.4	35	6	17.4
CCT-240	191-240	40	28.5	40	7	19
CCT-288	141-288	44.5	31.1	45	7	22.3
CCT-365	289-365	47.5	34	50	7	24.8
CCT-450	366-450	57	41	60	10	28
CCT-560	451-560	62	45	65	11	31
CCT-700	561-700	68	49.5	70	12	34